

Po zarejestrowaniu się w naszej sieci w panelu zarządzania w zakładce Ustawienia SIP znajdziesz login do usługi voip oraz hasło.

Program 3CXPhone5 można pobrać [tutaj](#)

Po zainstalowaniu uruchom program i kliknij prawym przyciskiem na ekran i wybierz accounts a potem edit.

Ustawienia dla 3CXPhone5 są następujące:

Account name: Dowolna nazwa

Caller ID: Dowolna nazwa

Extension: login do usługi voip (widoczny w zakładce ustawienia SIP w panelu)

ID: login do usługi voip (widoczny w zakładce ustawienia SIP w panelu)

Password: hasło (widoczne w zakładce ustawienia SIP w panelu)

I am in the office: sip.neotrix.pl

Po naciśnięciu OK, program zarejestruje się i można już dzwonić

Oto widok poprawnie skonfigurowanego programu:

**Account settings**

Account name:

Caller ID:

**Credentials**  
Enter your SIP account credentials

Extension:

ID:

Password:

**My location**  
Specify the IP of your PBX/SIP server

I am in the office - local IP  of PBX

I am out of the office - external IP  of PBX

Use 3CX Tunnel  
Eliminates firewall configuration. Requires 3CX Phone System for Windows

Local IP of remote PBX:

Tunnel password:  Port:

Use Outbound Proxy server  
Required by some VoIP Providers. Specify IP or name.

Perform provisioning from following URL:

Advanced settings    OK    Cancel